

128K DRAM kits

√26-5162 consists of eighteen 64K x 1 DRAM at 150 nanoseconds. This product can be obtained from Tandy National Parts under cat # 25-1000, part # AXX-7142.

256K DRAM kits

25-1079 consists of eight 256K x 1 DRAM at 150 nanoseconds.

Memory Boards

√25-1004 is a memory expansion board with 128K memory on board.

√25-1009 is a secondary memory expansion board with 128K memory on board. This product may be available from Tandy National Parts under cat # 25-1009, part # AX-9582. (Part # AX-9582 has 256K of memory).

√25-1011 is a memory expansion board with 256K memory on board. This product may be available from Tandy National Parts under cat # 25-1011, part # AX-2501011.

√ = Discontinued Radio Shack product.

Memory Upgrade:

| Tandy 1000A (25-1000A) - Expand from 128K: | | |
|--|--------------------|---------------------------|
| | Memory Adapter | Add to the Memory Adapter |
| 256K | 25-1004 | N/A |
| 384K | 25-1004 | AXX-7142 |
| 384K | 25-1011 | N/A |
| 512K | 25-1004 25-1009 | AXX-7142 N/A |
| 640K | 25-1004 25-1009 | AXX-7142 AXX-7142 |
| 640K | 25-1004 AX-9582 | AXX-7142 N/A |
| 640K | 25-1011 | 25-1079 |

| Jumper Settings for these Boards: | | | |
|-----------------------------------|------------|---------------------|--------------|
| Board | Memory Kit | Jumper | Memory Level |
| 25-1004 | AXX-7142 | no jumpers E1-E2 | 256K 384K |
| 25-1009 | | E3-E4 | 512K |

| | | | |
|---------|----------|---------------------|--------------|
| | AXX-7142 | E1-E2 & E3-E4 | 640K |
| 25-1011 | 25-1079 | E1-E2 no jumpers | 384K 640K |

(smm/jej-05/11/94)

□