

PIN	FUNCTION
1	Red Video
2	Green Video
3	Blue Video
4	Monitor ID Bit 2 (not used)
5	Ground
6	Red Return (ground)
7	Green Return (ground)
8	Blue Return (ground)
9	Key (no pin)
10	Sync Return (ground)
11	Monitor ID Bit 0 (not used)
12	Monitor ID Bit 1 (ground)
13	Horizontal Sync
14	Vertical Sync
15	Not Used

6
0
1 11
0 0
7
0
2 12
0 0
8
0
3 13
0 0
4 14
0 0
10
0
5 15
0 0

PARALLEL I/O PORT

PIN ASSIGNMENTS:

1	Strobe	10	ACKNOWLEDGE
2	Data Bit 0	11	BUSY
3	Data Bit 1	12	PAPER END
4	Data Bit 2	13	SELECT
5	Data Bit 3	14	AUTOFEED
6	Data Bit 4	15	ERROR
7	Data Bit 5	16	INITIALIZE
8	Data Bit 6	17	SELECT IN
9	Data Bit 7	18-25	Ground

KEYBOARD AND MOUSE CONNECTORS

PIN ASSIGNMENTS:

1	Data
2	Reserved
3	Ground
4	+5 Vdc
5	Clock
6	Reserved

RS232C SERIAL PORTS

PIN ASSIGNMENTS:

1	Carrier Detect
2	Receive Data
3	Transmit Data
4	Data Terminal Ready
5	Signal Ground
6	Data Set Ready
7	Request To Send
8	Clear To Send
9	Ring Indicator