

Large 15-Pin D-Shell Connector Pin Assignments

Pin	Signal
1	RCA Jack Audio 1
2	RCA Jack Video 1
3	Ground
4	RCA Jack Video 2
5	RCA Jack Audio 2 Left
6	Ground
7	Vertical Sync
8	Horizontal Sync
9	Stereo Phono Jack - Left Speaker
10	Stereo Phono Jack - Right Speaker
11	Ground
12	RCA Jack Audio 2 Right
13	Red
14	Green
15	Blue

Small 15-Pin D-Shell Connector Pin Assignments

Pin	Signal	Monochrome	Color
1	Red	No Pin	Red
2	Green	Mono Dots	Green
3	Blue	No Pin	Blue
4	Reserved	No Pin	No Pin
5	Digital Gnd	Self Test	Self Test
6	Red Return+	Key Pin	Red Return+
7	Green Return+	Mono Return	Green Return+
8	Blue Return+	No Pin	Blue Return+
9	Plug	No Pin	No Pin
10	Digital Gnd*	Digital Gnd*	Digital Gnd*
11	Reserved	No Pin	Digital Gnd*
12	Reserved	Digital Gnd*	No Pin
13	Horizontal Sync	Horizontal Sync	Horizontal Sync
14	Vertical Sync	Vertical Sync	Vertical Sync
15	Reserved	No Pin	No Pin

+Red Return, Green Return, Blue Return = Analog Ground

*Digital Ground-Digital Ground for sync returns and self test.

(DTC/jlc-03/23/94)

□